VS1 and VS4 Compatibility List

Table 1: Subassemblies

Manufacturer	Model	Description	Installation sheet
Edwards	D16L-VS	Sixteen-zone LED display expander	3101097-EN
	SA-232	RS-232 interface card	3101095-EN
	SA-CLA	Class A interface card	3101094-EN
	SA-DACT	Dialer	3101099-EN
	SA-ETH	Ethernet interface card	3101100-EN
	V-SLC2-1	Single SLC Interface card	3102228-EN
	V-SLC2-2	Dual SLC Interface card	3102200-EN

Table 2: Addressable detectors

Manufacturer	Model	Description
Edwards	B4U	Vigilant series standard base
	GSA-AB4G	Signature audible (sounder) base
	GSA-HFS	Signature fixed temperature heat detector
	GSA-HRS	Signature combination fixed temperature/rate-of-rise heat detector
	GSA-IB	Signature mounting base with fault isolator
	GSA-IB4	Signature mounting base with fault isolator, includes trim skirt
	GSA-IPHS	Signature combination ion/photo/heat detector
	GSA-IS	Signature ionization smoke detector
	GSA-PHS	Signature combination photo/heat detector
	GSA-PS	Signature photoelectric smoke detector
	GSA-RB	Signature detector mounting base with relay
	GSA-RB4	Signature detector mounting base with relay, includes trim skirt
	GSA-SB	Signature detector mounting base - standard
	GSA-SB4	Signature 4 in. detector mounting base, includes trim skirt
	GSA-SBT	Signature audible (sounder) base for CO and fire detectors
	GSA-SD	Signature SuperDuct photoelectric duct smoke detector
	IB4U	Vigilant series isolator detector base
	KI-ABDT	Fire-CO sounder base
	KI-ABLT	Low frequency sounder base
	KI-ABST	Sounder base

© 2018 United Technologies Corporation

P/N 3102354-EN • REV 006 • ISS 24JAN18

Manufacturer	Model	Description
	KI-IB	Signature mounting base with fault isolator
	KI-IB4	Signature mounting base with fault isolator, includes trim skirt
	KI-RB	Signature detector mounting base with relay
	KI-RB4	Signature detector mounting base with relay, includes trim skirt
	KI-SB	Signature detector mounting base - standard
	KI-SB4	Signature 4 in. detector mounting base, includes trim skirt
	KI-HFD	Signature fixed temperature heat detector
	KI-HRD	Signature combination fixed temperature/rate-of-rise heat detector
	KI-PCD	Signature photoelectric smoke detector with CO sensor
	KI-PHD	Signature combination photo/heat detector
	KI-PD	Signature photoelectric smoke detector
	RB4U	Vigilant series relay detector base
	SB4U	Vigilant series audible (sounder) detector base
	SB4U-LF, SB4U-LF-CA	Low frequency audible (sounder) base for fire detectors
	SIGA-AB4G-LF, SIGA-AB4G-LF-CA	Low frequency audible (sounder) base for CO and fire detectors
	V-HFD	Vigilant series fixed temperature heat detector
	V-HRD	Vigilant series rate-of-rise heat detector
	V-PCOS	Vigilant series combination photo/CO detector
	V-PCOS-CA	Vigilant series combination photo/CO detector (Canada)
	V-PHS	Vigilant series combination photo/heat detector
	V-PS	Vigilant series photoelectric smoke detector

Table 3: Addressable modules

Manufacturer	Model	Description
Edwards	GSA-M270	Signature single-action fire alarm station, English markings, metal
	GSA-M270P	Signature two-stage (presignal) fire alarm station, English markings, metal
	GSA-M278	Signature double-action, single-stage fire alarm station, plastic
	GSA-CC1	Signature single input signal module, two-gang standard mount
	GSA-CC1S	Signature single input signal synchronization module, two-gang standard mount
	GSA-CC2	Signature dual input signal module, two-gang standard mount
	GSA-CR	Signature control relay module, one-gang standard mount
	SIGA-CR2	Signature control relay module, dual terminals, one-gang standard mount
	GSA-CRR	Signature polarity reversal relay module, one-gang standard mount
	GSA-CRH	Signature high power control relay module
	GSA-CT1	Signature single input module, one-gang standard mount
	GSA-CT2	Signature dual input module, one-gang standard mount
	GSA-IM	Signature isolator module, two-gang standard mount
	GSA-IO	Signature input/output module, one-gang standard mount
	GSA-MAB	Signature universal Class A/B module, UIO plug-in
	GSA-MCC1	Signature single input signal module, UIO plug-in
	GSA-MCC1S	Signature single input signal synchronization module, UIO plug-in
	GSA-MCC2	Signature dual input signal module, UIO plug-in

Manufacturer	Model	Description
	GSA-MCR	Signature control relay module, UIO plug-in
	GSA-MCRR	Signature polarity reversal relay module, UIO plug-in
	GSA-MCT2	Signature dual input module, UIO plug-in
	GSA-MIO	Signature input/output module, UIO plug-in
	GSA-MM1	Signature monitor module, one-gang standard mount
	GSA-MRM1	Signature riser monitor module, UIO plug-in
	GSA-REL	Signature releasing module
	GSA-RM1	Signature riser monitor module, two-gang standard mount
	GSA-UM	Signature universal Class A/B module, two-gang standard mount
	GSA-WTM	Signature waterflow/tamper module, one-gang standard mount
	GSA-T3T4	Signature temporal pattern generator
	RZI16-2	Remote Zone Interface module

Table 4: Smoke detectors [1] [2]

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC (GSA-UM (ID 0.0 and 1.0) and GSA-MAB (ID 0.0 and 1.0)	Max. per IDC (RZI16-2)
Edwards	1151	Ionization smoke detector	N/A	N/A	N/A	24
	1400	Ionization smoke detector	N/A	N/A	N/A	24
	1451	Photoelectric smoke detector	N/A	N/A	N/A	28
	2151	Photoelectric smoke detector	N/A	B110LP, B401B	N/A	29
	2151T	Photoelectric smoke detector	N/A	B110LP, B401B	N/A	24
	2420	Ionization smoke detector	100 / N/A	N/A	N/A	46
	2430	Photoelectric smoke detector	100 / N/A	N/A	N/A	46
	2432B	Combination photoelectric smoke/heat detector	100 / N/A	N/A	N/A	46
	2435P	Photoelectric duct smoke detector	100 / N/A	Included	N/A	46
	2451	Photoelectric smoke detector	N/A / N/A	N/A	N/A	24
	2M-PD	Photoelectric smoke detector	S10A	N/A	N/A	30
	2M-PDC	Photoelectric smoke detector	S10A	N/A	N/A	30
	2M-PDHC	Photoelectric smoke detector with FT and ROR heat	S10A	N/A	N/A	30
	2M-PDHRC	Photoelectric smoke detector with FT and ROR heat and auxiliary relay	S10A	N/A	N/A	30
	2WB	Photoelectric smoke detector	N/A	N/A	N/A	24
	2WT-B	Photoelectric smoke detector	N/A	N/A	N/A	24
	2WTA-B	Photoelectric smoke detector	N/A	N/A	N/A	24
	429C	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	10	30
	429CRT	Photoelectric smoke detector (12/24 VDC) with dual heat sensor (FT/ROR) and auxiliary relay	S11A	N/A	N/A	1

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC (GSA-UM (ID 0.0 and 1.0) and GSA-MAB (ID 0.0 and 1.0)	Max. per IDC (RZI16-2)
	429CST	Photoelectric smoke detector (12/24 VDC) with dual heat sensor (FT/ROR) and sounder	S11A	N/A	N/A	1
	429CT	Photoelectric smoke detector (12/24 VDC) with dual heat sensor (FT/ROR)	S10A / N/A	N/A	10	30
	511C	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	10	30
	521B	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	10	30
	521BXT	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/ROR)	S10A / N/A	N/A	10	30
	521CRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/ROR), and auxiliary relay	S11A	N/A	N/A	1
	521NC	Photoelectric smoke detector with CleanMe (8.5 to 33 VDC)	S10A	N/A	10	10
	521NCXT	Photoelectric smoke detector with CleanMe, fixed temperature and rate of rise heat (8.5 to 33 VDC)	S10A	N/A	10	10
	521NCRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/ROR), and auxiliary relay	S11A	N/A	N/A	1
	521NCSRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/ROR), auxiliary relay, and sounder	S11A	N/A	N/A	1
	521NCSXT	Photoelectric smoke detector with CleanMe, fixed temperature and rate of rise heat, with sounder (8.5 to 33 VDC)	S10A / N/A	N/A	10	30
	528B	Photoelectric smoke detector (12/24 VDC) with CleanMe	N/A / N/A	N/A	10	30
	528BXT	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/ROR)	N/A / N/A	N/A	10	30
	528CRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual FT/ROR heat sensor, and auxiliary relay	S11A	N/A	N/A	1
	5151	Rate of rise Heat Detector	N/A	B110LP, B401B	N/A	24
	6249B	Ionization smoke detector and base	001	N/A	N/A	45
	6249C	Ionization smoke detector and base	N/A	N/A	N/A	45
	6250B	Ionization smoke detector	001	6249B-001 6251B-001A	N/A	45
	6250C	Ionization smoke detector	N/A	6249B-001 6251B-001A	N/A	45
	6264B-001 [3]	Ionization duct smoke detector	001	6251B-001A	N/A	45
	6264C-001 [3]	Ionization duct smoke detector	001	6251B-001A	N/A	45
	6266B-001	Photoelectric duct smoke detector	_001	N/A	N/A	24
	6266C-001 [3]	Photoelectric duct smoke detector	001	6251B-001A	N/A	24

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC (GSA-UM (ID 0.0 and 1.0) and GSA-MAB (ID 0.0 and 1.0)	Max. per IDC (RZI16-2)
	6269B	Photoelectric smoke detector and base	001	N/A	N/A	24
	6269B-003	Photoelectric smoke-heat detector and base	001	N/A	N/A	21
	6269C	Photoelectric smoke detector and base	N/A	N/A	N/A	21
	6269C-003	Photoelectric smoke-heat detector and base	N/A	N/A	N/A	21
	6270B	Photoelectric smoke detector	001	6249B-001 6251B-001A	N/A	21
	6270B-003	Combination photoelectric smoke-heat detector	001	6249B-001 6251B-001A	N/A	21
	6270C	Photoelectric smoke detector	_001	N/A	N/A	21
	6270C-003	Combination Photoelectric smoke-heat detector	_001	N/A	N/A	21
	711U	Photoelectric smoke detector (12/24 VDC)	S10A/S00	701U, 702E, 702U	10	30
	711UT	Fast response photoelectric smoke detector (12/24 VDC) with heat sensors	S10A/S00	701U, 702E, 702U	10	30
	713-5U	Two-wire rate-of-rise and 57°C (135°F) fixed temperature heat detector	S10A/S00	701U, 702E, 702U	10	30
	721UT	Fast response photoelectric smoke detector (12/24 VDC) with remote alarm/trouble LED	S10A/S00	701U, 702E, 702U	10	30
	731U	Photoelectric smoke detector (12/24 VDC) with auxiliary relay	S11A	N/A	N/A	1
	73405-001 [3]	Ionization duct smoke detector	001A	73486U	20	45
	73405U-001 [3]	Ionization duct smoke detector	001A	73486U	20	45
	73494	Ionization smoke detector and base	N/A / N/A	N/A	20	45
	73494-001	Smoke detector	_001	N/A	N/A	24
	73494U	Ionization smoke detector and base	001 / N/A	N/A	N/A	45
	73494U-001 [3]	Ionization smoke detector and base	_001	N/A	N/A	24
	73495	Ionization smoke detector	N/A / N/A	73486U	20	45
	73495U	Ionization smoke detector	001/001	73486U	20	45
	73575	Photoelectric smoke detector and base	N/A / N/A	N/A	10	24
	73575U	Photoelectric smoke detector and base	001 / N/A	N/A	10	24
	73576	Photoelectric smoke/heat detector and base	N/A / N/A	N/A	10	21
	73576U	Photoelectric smoke/heat detector and base	001 / N/A	N/A	10	21
	73594-001	Photoelectric duct smoke detector	001/001	73486U	10	24
	73594U-001 [3]	Photoelectric duct smoke detector	001/001	73486U	10	24
	73595	Photoelectric smoke detector	N/A / 001	73486U	10	21
	73595U	Photoelectric smoke detector	001/001	73486U	10	21

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC (GSA-UM (ID 0.0 and 1.0) and GSA-MAB (ID 0.0 and 1.0)	Max. per IDC (RZI16-2)
	73596	Combination photoelectric smoke/heat detector	N/A / 001	73486U	10	21
	73596U	Combination photoelectric smoke/heat detector	001/001	73486U	10	21
	C2M-PD	Photoelectric smoke detector	S09A	N/A	N/A	30
	C2M-PDC	Photoelectric smoke detector	S09A	N/A	N/A	30
	C2M-PDHC	Photoelectric smoke detector with FT and ROR heat	S09A	N/A	N/A	30
	C2M-PDHRC	Photoelectric smoke detector with FT and ROR heat and auxiliary relay	S11A	N/A	N/A	1
	EC10U-3	24V Ion detector	A	N/A	N/A	46
	EC20FTU-3	Fixed temperature heat detector, 135°F (58°C)	A	N/A	N/A	46
	EC20RRU-3	Rate of rise heat detector, 135°F (58°C)	A	N/A	N/A	46
	EC30DU-3 [6]	Photoelectric duct smoke detector	A/A	CSBU-1, CSBU-3	16	48
	EC30U-3	Photoelectric smoke detector	A	N/A	N/A	48
	ED2M-PD	Photoelectric smoke detector (12/24 VDC)	S10A	N/A	N/A	30
	ED2M-PDC	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	N/A	30
	ED2M-PDHC	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/ROR)	S10A / N/A	N/A	N/A	30
	EDW1151A	Ionization smoke detector	N/A	N/A	N/A	24
	EDW1400A	Ionization smoke detector	N/A	N/A	N/A	24
	EDW1451A	Ionization smoke detector	N/A	N/A	N/A	24
	EDW2151A	Photoelectric smoke detector	N/A	N/A	N/A	24
	EDW2451A	Photoelectric smoke detector	N/A	N/A	N/A	24
	ESD-2W	SuperDuct photoelectric duct smoke detector	_0.0	N/A	N/A	42
	FX7-2	Photoelectric smoke detector and base	S10A	N/A	N/A	30
	FX7-2R	Photoelectric smoke detector, base, and auxiliary relay	S11A	N/A	N/A	1
	FX7-2T	Photoelectric smoke detector and base, ROR heat detector, remote test, alarm/trouble LED output	S10A	N/A	N/A	30
	M2M-PD	Photoelectric smoke detector	S10A	N/A	N/A	30
	M2M-PDC	Photoelectric smoke detector	S10A	N/A	N/A	30
	M2M-PDHC	Photoelectric smoke detector	S10A	N/A	N/A	30
	MC10U-03 [5]	Ionization smoke detector	A/A	CSBU-1, CSBU-3, CSB4U-1	20	46
	MC20FTU-03	Fixed temperature heat detector, 135°F (58°C)	A/A	CSBU-1, CSBU-3, CSB4U-1	15	46

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC (GSA-UM (ID 0.0 and 1.0) and GSA-MAB (ID 0.0 and 1.0)	Max. per IDC (RZI16-2)
	MC20RRU-03	Rate of rise heat detector, 135°F (58°C)	A/A	CSBU-1, CSBU-3, CSB4U-1	15	46
	MC30U-03 [5]	Photoelectric smoke detector	A/A	CSBU-1, CSBU-3, CSB4U-1	16	48
	MT1151A	Ionization smoke detector	N/A / N/A	MTB110LP	8	24
	MT1400A	Ionization smoke detector	N/A / N/A	N/A	8	24
	MT1451A	Photoelectric smoke detector	N/A / N/A	MTB401B	8	24
	MT2151A	Photoelectric smoke detector	N/A / N/A	MTB110LP	8	24
	MT2451A	Photoelectric smoke detector	N/A / N/A	MTB401B	8	24
	SC10U-3	Ionization smoke detector	A	N/A	N/A	46
	SC20RRU-3	Rate of rise heat detector, 135°F (58°C)	A	N/A	N/A	46
	SC20FTU-3	Fixed temperature heat detector, 135°F (58°C)	A / A	CSBU-1, CSBU-3, CSB4U-1	N/A	46
	SC30DU-3	Photoelectric duct smoke detector	A	N/A	N/A	48
	SD-2W [4]	SuperDuct photoelectric duct smoke detector	0.0 / N/A	N/A	14	42
	TS7-2	Photoelectric smoke detector (12/24 VDC) and base	S10A	N/A	N/A	30
	TS7-2R	Photoelectric smoke detector (12/24 VDC) with auxiliary relay and base	S11A	N/A	N/A	1
	TS7-2T	Fast response photoelectric smoke detector (12/24 VDC) with remote alarm/trouble LED and base	S10A	N/A	N/A	30

[1] Do not install different smoke detector models on the same circuit
[2] Do not install dry contact devices on the same circuit as smoke detectors if the circuit is configured for alarm verification
[3] Requires a compatible base and 73401A housing
[4] Do not install on circuits configured for alarm verification
[5] Do not install on circuits configured for alarm verification unless installed in a resistor base
[6] Requires a compatible base and 6260A-CU housing

Table 5: Notification appliances

Manufacturer	Model	Description	Audible sync	Visible sync
Edwards	403-3A-R, 403-5A-R, 403-7A-R, 403-8A-R, 2453BSA-30-R, 2453BSA-15/75-R, 2453BSA-110-R	Integrity bell/strobe plate	Y	Y
	405-3A-T, 405-3A-TW, 405-5A-T, 405-5A-TW, 405-6A-T, 405-6A-TW, 405-7A-T, 405-7A-TW, 405-8A-T, 405-8A-TW, CS405-7A-T, CS405-8A-T	Integrity synchronized strobe	N/A	Y
	4MS-3AR, 4MS-3AW, 4MS-5AR, 4MS-5AW, 4MS-6AR, 4MS-6AW, 4MS-7AR, 4MS-7AW, 4MS-8AR, 4MS-8AW, 2441S-30-R, 2441S-30-W, 2441S-15-R, 2441S-15-W, 2441S-60-R, 2441S-60-W, 2441S-15/75-R, 2441S-15/75-W, 2441S-110-R, 2441S-110-W	Integrity synchronized strobe	N/A	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	757-1A-R25, 757-1A-R25W, 757-1A-R70, 757-1A-R70W, INT-R2, INT-R2W, INT-R, INT-RW	Integrity re-entrant speaker	N/A	N
	757-1A-S25, 757-1A-S25W, 757-1A-S70, 757-1A-S70W, INT-S2, INT-S2W, INT-S, INT-SW	Integrity cone type speaker	N/A	N
	757-3A-RS25, 757-3A-RS25W, 757-3A-RS70, 757-3A-RS70W, INT-3AR2, INT-3AR2W, INT-3AR, INT-3ARW	Integrity re-entrant speaker/strobe 30 cd	N/A	Y
	757-5A-RS25, 757-5A-RS25W, 757-5A-RS70, 757-5A-RS70W, INT-5AR2, INT-5AR2W, INT-5AR, INT-5ARW	Integrity re-entrant speaker/strobe 15 cd	N/A	Y
	757-7A-RS25, 757-7A-RS25W, 757-7A-RS70, 757-7A-RS70W, INT-7AR2, INT-7AR2W, INT-7AR, INT-7ARW	Integrity re-entrant speaker/strobe 15/75 cd	N/A	Y
	757-8A-RS25, 757-8A-RS25W, 757-8A-RS70, 757-8A-RS70W, INT-8AR2, INT-8AR2W, INT-8AR, INT-8ARW	Integrity re-entrant speaker/strobe 110 cd	N/A	Y
	964-1A-4RR, 964-1A-4RW, CS2-1A4RR, CS2-1A4R, 965-1A-4RR, 965-1A-4RW, CS7-1A4RR, CS7-1A4R	4 in. speakers	N/A	N
	964-1A-8SW, 964-1A-8RW, CS2-1A8S, CS2-1A8R, 965-1A-8SW, 965-1A-8RW, CS7-1A8S, CS7-1A8R	8 in. speakers	N/A	N
	964-3A-4RR, 964-3A-4RW, CSS2-3A4RR, CSS2-3A4R, 965-3A-4RR, 965-3A-4RW, CSS7-3A4RR, CSS7-3A4R	4 in. 30 cd speaker/strobe	N/A	Y
	964-3A-8RW, 964-3A-8SW, CSS2-3A8R, CSS2-3A8S, 965-3A-8RW, 965-3A-8SW, CSS7-3A8R, CSS7-3A8S	8 in. 30 cd speaker/strobe	N/A	Y
	964-5A-4RR, 964-5A-4RW, CSS2-5A4RR, CSS2-5A4R, 965-5A-4RR, 965-5A-4RW, CSS7-5A4RR, CSS7-5A4R	4 in. 15 cd speaker/strobe	N/A	Y
	964-5A-8RW, 964-5A-8SW, CSS2-5A8R, CSS2-5A8S, 965-5A-8RW, 965-5A-8SW, CSS7-5A8R, CSS7-5A8S	8 in. 15 cd speaker/strobe	N/A	Y
	964-7A-4RR, 964-7A-4RW, CSS2-7A4RR, CSS2-7A4R, 965-7A-4RR, 965-7A-4RW, CSS7-7A4RR, CSS7-7A4R	4 in. 15/75 cd speaker/strobe	N/A	Y
	964-7A-8RW, 964-7A-8SW, CSS2-7A8R, CSS2-7A8S, 965-7A-8RW, 965-7A-8SW, CSS7-7A8R, CSS7-7A8S	8 in. 15/75 cd speaker/strobe	N/A	Y
	964-8A-4RR, 964-8A-4RW, CSS2-8A4RR, CSS2-8A4R, 965-8A-4RR, 965-8A-4RW, CSS7-8A4RR, CSS7-8A4R	4 in. 110 cd speaker/strobe	N/A	Y
	964-8A-8RW, 964-8A-8SW, CSS2-8A8R, CSS2-8A8S, 965-8A-8RW, 965-8A-8SW, CSS7-8A8R, CSS7-8A8S	8 in. 110 cd speaker/strobe	N/A	Y
	CGC-S2VM, CGCF-S2VM	Speaker-strobe, 25 VRMS, 15 to 95 multi-cd, white [3]	N/A	Y
	CGC-S2VMH, CGCF-S2VMH	Speaker-strobe, 25 VRMS, 95 to 177 multi-cd, white [3]	N/A	Y
	CGC-S7VM, CGCF-S7VM	Speaker-strobe, 70 VRMS, 15 to 95 multi-cd, white [3]	N/A	Y
	CGC-S7VMH, CGCF-S7VMH	Speaker-strobe, 70 VRMS, 95 to 177 multi-cd, white [3]	N/A	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	EG1-C, EG1R-C, EG1F-C, EG1RF-C, G1-C, G1R-C, G1F-C, G1RF-C, MG1-C, MG1R-C, MG1F-C, MG1RF-C	Genesis chimes	N/A	N/A
	EG1-CVM, EG1R-CVM, EG1F-CVM, EG1RF-CVM, G1-CVM, G1R-CVM, G1F-CVM, G1RF-CVM, MG1-CVM, MG1F-CVM, MG1R-CVM MG1RF-CVM	Genesis chime/strobes, 15 to 110 cd	N/A	Y
	EG1F-CV1575, G1F-CV1575, MG1F-CV1575	Genesis chime/strobe, low or high dBA, 15 or 75 cd	N/A	Y
	EG1F-HDV1575, EG1RF-HDV1575, G1F-HDV1575 MG1F-HDV1575, MG1RF-HDV1575	Genesis temporal horn/strobe, low or high dBA, 15 or 75 cd	Y	Y
	EG1-H, EG1R-H, EG1-HO, EG1R-HO, EG1F-HO, EG1RF-HO, G1-H, G1R-H, G1-HO, G1R-HO, G1F-HO, G1RF-HO, MG1-H, MG1R-H, MG1-HO, MG1R-HO, MG1F-HO, MG1RF-HO	Genesis temporal horns	Y	N
	EG1-HD, EG1R-HD, EG1F-HD, EG1RF-HD, G1-HD, G1R-HD, G1F-HD, G1RF-HD, MG1-HD, MG1R-HD, MG1F-HD, MG1RF-HD	Genesis temporal horns	Y	N/A
	EG1-HDVM, EG1R-HDVM, EG1F-HDVM, EG1RF-HDVM, G1-HDVM, G1R-HDVM, G1F-HDVM, G1RF-HDVM, MG1-HDVM, MG1R-HDVM, MG1F-HDVM, MG1RF-HDVM	Genesis temporal horn/strobes, 15 to 110 cd	Y	Y
	EG1-HDVM-A, G1-HDVM-A, MG1-HDVM-A	Genesis temporal horn/strobe, 15 to 110 cd, selectable lenses	Y	Y
	EG1-HDVM-RCC, G1-HDVM-RCC, MG1-HDVM-RCC	Genesis temporal horn/strobe, ceiling mount 15 to 110 cd, private mode only	Y	Y
	EG1-HOV110, EG1R-HOV110, EG1F-HOV110, EG1RF-HOV110, G1-HOV110, G1R-HOV110, G1F-HOV110, G1RF-HOV110, MG1-HOV110, MG1R-HOV110, MG1F-HOV110, MG1RF-HOV110	Genesis temporal horn/strobes, high dBA, 110 cd	Y	Y
	EG1-HOV110R, G1-HOV110R, MG1-HOV110R	Genesis temporal horn/strobe, 52 cd, private mode only	Y	Y
	EG1-HOV15, EG1R-HOV15, EG1F-HOV15, EG1RF-HOV15, G1-HOV15, G1R-HOV15, G1F-HOV15, G1RF-HOV15, MG1-HOV15, MG1R-HOV15, MG1F-HOV15, MG1RF-HOV15	Genesis temporal horn/strobes, high dBA, 15 cd	Y	Y
	EG1-HOV30, EG1R-HOV30, EG1F-HOV30, EG1RF-HOV30, G1-HOV30, G1R-HOV30, G1F-HOV30, G1RF-HOV30, MG1-HOV30, MG1R-HOV30, MG1F-HOV30, MG1RF-HOV30	Genesis temporal horn/strobes, high dBA, 30 cd	Y	Y
	EG1-HOV60, EG1R-HOV60, EG1F-HOV60, EG1RF-HOV60, G1-HOV60, G1R-HOV60, G1F-HOV60, G1RF-HOV60, MG1-HOV60, MG1R-HOV60, MG1F-HOV60, MG1RF-HOV60	Genesis temporal horn/strobes, high dBA, 60 cd	Y	Y
	EG1-HOV75, EG1R-HOV75, EG1F-HOV75, EG1RF-HOV75, G1-HOV75, G1R-HOV75, G1F-HOV75, G1RF-HOV75, MG1-HOV75, MG1R-HOV75, MG1F-HOV75, MG1RF-HOV75	Genesis temporal horn/strobes, high dBA, 75 cd	Y	Y
	EG1-HV15, EG1R-HV15, G1-HV15, G1R-HV15, MG1-HV15, MG1R-HV15	Genesis temporal horn/strobes, low dBA, 15 cd	Y	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	EG1-HV30, EG1R-HV30, G1-HV30, G1R-HV30, MG1-HV30, MG1R-HV30	Genesis temporal horn/strobes, low dBA, 30 cd	Y	Y
	EG1-HV60, EG1R-HV60, G1-HV60, G1R-HV60, MG1-HV60, MG1R-HV60	Genesis temporal horn/strobes, low dBA, 60 cd	Y	Y
	EG1-HV75, EG1R-HV75, G1-HV75, G1R-HV75, MG1-HV75, MG1R-HV75	Genesis temporal horn/strobes, low dBA, 75 cd	Y	Y
	EG1-P, EG1R-P, EG1F-P, EG1RF-P, G1-P, G1R-P, G1F-P, G1RF-P, MG1-P, MG1R-P, MG1F-P, MG1RF-P	Genesis horns	Y	N
	EG1R-HDVM-RCW, G1R-HDVM-RCW, MG1R-HDVM-RCW	Genesis temporal horn/strobe, wall mount, 15 to 110 cd, private mode only	Y	Y
	EG1R-VM-RCW, G1R-VM-RCW, MG1R-VM-RCW	Genesis strobe, wall mount, 15 to 110 cd, private mode only	N/A	Y
	EG1-V110, EG1R-V110, EG1F-V110, EG1RF-V110 G1-V110, G1R-V110, G1F-V110, G1RF-V110, MG1-V110, MG1R-V110, MG1F-V110, MG1RF-V110	Genesis strobes, 110 cd	N/A	Y
	EG1-V15, EG1R-V15, EG1F-V15, EG1RF-V15, G1-V15, G1R-V15, G1F-V15, G1RF-V15, MG1-V15, MG1R-V15, MG1F-V15, MG1RF-V15EG1-V15	Genesis strobes, 15 cd	N/A	Y
	EG1-V30, EG1R-V30, EG1F-V30, EG1RF-V30, G1-V30, G1R-V30, G1F-V30, G1RF-V30, MG1-V30, MG1R-V30, MG1F-V30, MG1RF-V30	Genesis strobes, 30 cd	N/A	Y
	EG1-V60, EG1R-V60, EG1F-V60, EG1RF-V60, G1-V60, G1R-V60, G1F-V60, G1RF-V60, MG1-V60, MG1R-V60, MG1F-V60, MG1RF-V60	Genesis strobes, 60 cd	N/A	Y
	EG1-V75, EG1R-V75, EG1F-V75, EG1RF-V75, G1-V75, G1R-V75, G1F-V75, G1RF-V75, MG1-V75, MG1R-V75, MG1F-V75, MG1RF-V75	Genesis strobes, 75 cd	N/A	Y
	EG1-VM, EG1R-VM, EG1F-VM, EG1RF-VM, G1-VM, G1R-VM, G1F-VM, G1RF-VM, MG1-VM, MG1R-VM, MG1F-VM, MG1RF-VM	Genesis strobes, 15 to 110 cd	N/A	Y
	EG1-VM-A, G1-VM-A, MG1-VM-A	Genesis strobe, 15 to 110 cd, selectable lenses	N/A	Y
	EG1-VM-RCC, G1-VM-RCC, MG1-VM-RCC	Genesis strobe, ceiling mount, 15 to 110 cd, private mode only	N/A	Y
	EG4-S2VM, EG4R-S2VM, EG4F-S2VM, EG4RF-S2VM, G4-S2VM, G4R-S2VM, G4F-S2VM, G4RF-S2VM, MG4-S2VM, MG4R-S2VM, MG4F-S2VM, MG4RF-S2VM	Genesis speaker/strobe, 25 VRMS, 15 to 110 cd	N/A	Y
	EG4-S7VM, EG4R-S7VM, EG4F-S7VM, EG4RF-S7VM, G4-S7VM, G4R-S7VM, G4F-S7VM, G4RF-S7VM, MG4-S7VM, MG4R-S7VM, MG4F-S7VM, MG4RF-S7VM	Genesis speaker/strobe, 70 VRMS, 15 to 110 cd	N/A	Y
	EGC-HDVM, EGCF-HDVM, EGCRF-HDVM, GC-HDVM, GCF-HDVM, MGC-HDVM, MGCF-HDVM, MGCRF-HDVM	Genesis ceiling horn/strobe, 15 to 95 cd	Y	Y
	EGC-HDVMH, EGCF-HDVMH, GC-HDVMH, GCF-HDVMH, MGC-HDVMH, MGCF-HDVMH	Genesis ceiling horn/strobe, 95 to 177 cd	Y	Y
	EGC-S2VM, EGCF-S2VM, GC-S2VM, GCF-S2VM, MGC-S2VM, MGCF-S2VM	Genesis ceiling speaker/strobe, 25 VRMS, 15 to 95 cd	N/A	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	EGC-S2VMH, EGCF-S2VMH, GC-S2VMH, GCF-S2VMH, MGC-S2VMH, MGCF-S2VMH	Genesis ceiling speaker/strobe, 25 VRMS, 95 to 177 cd	N/A	Y
	EGC-S7VM, EGCF-S7VM, GC-S7VM, GCF-S7VM, MGC-S7VM, MGCF-S7VM	Genesis ceiling speaker/strobe, 70 VRMS, 15 to 95 cd	N/A	Y
	EGC-S7VMH, EGCF-S7VMH, GC-S7VMH, GCF-S7VMH, MGC-S7VMH, MGCF-S7VMH	Genesis ceiling speaker/strobe, 70 VRMS, 95 to 177 cd	N/A	Y
	EGC-VM, EGCF-VM, EGCRF-VM, GC-VM, GCF-VM, MGC-VM, MGCF-VM, MGCRF-VM	Genesis ceiling strobes, 15 to 95 cd	N/A	Y
	EGC-VMH, EGCF-VMH, GC-VMH, GCF-VMH, MGC-VMH, MGCF-VMH	Genesis ceiling strobes, 95 to 177 cd	N/A	Y
	G1F-V1575, EG1F-V1575, EG1RF-V1575, MG1F-V1575, MG1RF-V1575	Genesis strobe, 15 or 75 cd	N/A	Y
	G4HFWA-S2VMA, G4HFWN-S2VMA, G4HFWA-S7VMA, G4HFWN-S7VMA	Genesis high fidelity low frequency speaker/strobe	N/A	Y
	G4HFWA-S2VMC, G4HFWA-S7VMC, GCHFWA-S2VMC, GCHFWA-S2VMCH, GCHFWA-S7VMC, GCHFWA-S7VMCH	Genesis high fidelity low frequency speaker/strobe	N/A	Y
	G4HFWN-S2VMC, G4HFRN-S2VMC, G4HFWF-S2VMC, G4HFRF-S2VMC, G4HFWN-S7VMC, G4HFRN-S7VMC, G4HFWF-S7VMC, G4HFRF-S7VMC	Genesis high fidelity low frequency speaker/strobe	N/A	Y
	G4LFRF-H, G4LFRN-H, G4LFWF-H, G4LFWN-H	Genesis low frequency (520 Hz) horn, temporal or steady, low or high dB	Y	N/A
	G4LFRF-HVM, G4LFRN-HVM, G4LFWF-HVM, G4LFWN-HVM	Genesis low frequency (520 Hz) horn-strobe, temporal or steady, low or high dB, 15 to 110 cd	Y	Y
	GCHFRF-S2VMC, GCHFWF-S2VMC, GCHFRN-S2VMC, GCHFWN-S2VMC, GCHFRF-S2VMCH, GCHFWF-S2VMCH, GCHFRN-S2VMCH, GCHFWN-S2VMCH, GCHFRF-S7VMC, GCHFWF-S7VMC, GCHFRN-S7VMC, GCHFWN-S7VMC, GCHFRF-S7VMCH, GCHFWF-S7VMCH, GCHFRN-S7VMCH, GCHFWN-S7VMCH	Genesis high fidelity low frequency speaker/strobe	N/A	Y
	GCHFWA-S2VMA, GCHFWN-S2VMA, GCHFWA-S2VMAH, GCHFWN-S2VMAH, GCHFWA-S7VMA, GCHFWN-S7VMA, GCHFWA-S7VMAH, GCHFWN-S7VMAH	Genesis high fidelity low frequency speaker/strobe	N/A	Y
	GL1RF-HD, GL1RN-HD, GL1WF-HD, GL1WN-HD	Genesis GL-Series horn, temporal or steady, low or high dB	Y	N/A
	GL1RF-HDVMC, GL1RN-HDVMC, GL1WF-HDVMC, GL1WN-HDVMC	Genesis GL-Series horn-strobe, temporal or steady, low or high dB, LED strobe, 15 to 110 cd	Y	Y
	GL1RF-VMC, GL1RN-VMC, GL1WF-VMC, GL1WN-VMC	Genesis GL-Series strobe, LED strobe, 15 to 110 cd	N/A	Y
	INT-3AC, INT-3ACW, INT-5AC, INT-5ACW, INT-7AC, INT-7ACW, INT-8AC, INT-8ACW	Integrity synchronized chime/strobes	N/A	Y
	INT-3AT, INT-3ATW, INT-5AT, INT-5ATW, INT-7AT, INT-7ATW, INT-8AT, INT-8ATW, 757-3A-T, 757-3A-TW, 757-5A-T, 757-5A-TW, 757-7A-T, 757-7A-TW, 757-8A-T, 757-8A-TW, 2452THS-30-R, 2452THS-30-W, 2452THS-15-R, 2452THS-15-W, 2452THS-15/75-R, 2452THS-15/75-W, 2452THS-110-R, 2452THS-110-W	Integrity synchronized temporal horn/strobes	Y	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	INT-C, INT-CW,	Integrity chimes	N/A	N/A
	INTH-15PS, INTH-15PSW, INTH-75PS, INTH-75PSW,	Power saver synchronized temporal horn/strobes	Y	Y
	MHS-3AR, MHS-3AW, MHS-5AR, MHS-5AW, MHS-7AR, MHS-7AW, MHS-8AR, MHS-8AW	Mini horn/strobes	Y	Y
	MS-15PS, MS-15PSW, MS-75PS, MS-75PSW	Power saver synchronized strobes	N/A	Y
	MS-3AR, MS-3AW, MS-5AR, MS-5AW, MS-6AR, MS-6AW, MS-7AR, MS-7AW, MS-8AR, MS-8AW, 202-3A-T, 202-3A-TW, 202-5A-T, 202-5A-TW, 202-6A-T, 202-6A-TW, 202-7A-T, 202-7A-TW, 202-8A-T, 202-8A-TW, 2440S-15/75-R, 2440S-15/75-W, 2440S-110-W, 2440S-110-R	Integrity synchronized strobes	N/A	Y
	WG4RF-H, WG4WF-H, WG4RN-H, WG4WN-H	Outdoor Genesis horn	Y	N
	WG4RF-HVMC, WG4RN-HVMC, WG4WF-HVMC, WG4WN-HVMC	Outdoor Genesis horn/strobe, 15/29/70/87 cd [1]	Y	Y
	WG4RF-HVMHC, WG4RN-HVMHC, WG4WF-HVMHC, WG4WN-HVMHC	Outdoor Genesis horn/strobe. 102/123/147/161 cd [1]	Y	Y
	WG4RF-SVMC, WG4RN-SVMC, WG4WA-SVMC, WG4WF-SVMC, WG4WN-SVMC	Outdoor Genesis speaker/strobe, 25/70 VRMS, 15/29/70/87 cd [1] [2]	N/A	Y
	WG4RF-SVMHC, WG4RN-SVMHC, WG4WA-SVMHC, WG4WF-SVMHC, WG4WN-SVMHC	Outdoor Genesis speaker/strobe. 25/70 VRMS, 102/123/147/161 cd [1] [2]	N/A	Y

[1] When metallic conductors are installed that extend beyond one building, the circuits are *required* to be protected with UL 497B listed transient protectors with the appropriate voltage ratings for the circuit being protected. When notification appliances are installed outside of a building (e.g. mounted on an exterior wall) and are connected to an interior circuit that may not have transient protection, it is *recommended* that these circuits also be protected with UL 497B listed transient protection with the appropriate voltage ratings for the circuit being protected. Consult applicable codes for further information.
[2] UL only
[3] ULC only

Table 6: Accessories

Manufacturer	Model	Description
Edwards	6254A-003	Auxiliary relay
	CTM	City tie module
	E-RLCD	Remote LCD annunciator, acknowledge/silence and lamp test buttons, white, English
	E-RLCD-C	Remote LCD annunciator, common controls, white, English
	E-RLED-C	Remote LED annunciator, 16 zones, common controls, white, English
	GCI	Graphic annunciator driver card
	GCIX	GCI expander card
	GSA-UIO2R, GSA-UIO6, GSA-UIO6R	Universal input/output module motherboard for UIO plug-in modules
	K-RLCD	LCD text annunciator without common controls, white, English
	K-RLCD-C	LCD text annunciator with common controls, white, English
	K-RLCD-CR	LCD text annunciator with common controls, red, English
	K-RLCD-R	LCD text annunciator without common controls, red, English
	K-RLED24	24-pair LED zone expander with expander cable and zone card insert, white

Manufacturer	Model	Description
	K-RLED24R	24-pair LED zone expander with expander cable and zone card insert, red
	K-RLED-C	16-pair LED zone annunciator with common controls, white, English
	K-RLED-CR	16-pair LED zone annunciator with common controls, red, English
	K-RLCD-CF	LCD text annunciator with common controls, French
	K-RLCD-C-PG	LCD text annunciator with common controls, Portuguese
	K-RLCD-C-SP	LCD text annunciator with common controls, Spanish
	K-RLCDF	LCD text annunciator without common controls, French
	K-RLCD-PG	LCD text annunciator without common controls, Portuguese
	K-RLCD-SP	LCD text annunciator without common controls, Spanish
	K-RLED-CF	16-pair LED zone annunciator with common controls, French
	K-RLED-C-PG	16-pair LED zone annunciator with common controls, Portuguese
	K-RLED-CR	16-pair LED zone annunciator with common controls, red, English
	K-RLED-C-SP	16-pair LED zone annunciator with common controls, Spanish
	MG1M	Genesis synchronization module
	MG1M-RM	Genesis synchronization module, remote mount
	MR-101/C, MR-101/T	Single multivoltage control relay module, SPDT
	MR-104/C, MR-104/T	Four multivoltage control relay module, SPDT
	MR-201/C, MR-201/T	Single multivoltage control relay module, DPDT
	MR-204/C, MR-204/T	Four multivoltage control relay module, DPDT
	PAM-1	Multivoltage control relay
	PT-1S	System event printer (serial)
	RA-ENC1	Annunciator cabinet, surface mount, holds one remote annunciator
	RA-ENC2	Annunciator cabinet, surface mount, holds one remote annunciator and one remote expander
	RA-ENC3	Annunciator cabinet, surface mount, holds one remote annunciator and two remote expanders
	RKEY	Remote annunciator enable key switch
	RLCD(F)	Remote LCD annunciator, acknowledge/silence and lamp test buttons, white, (French)
	RLCD-C(F)	Remote LCD annunciator, common controls, white, (French)
	RLCD-CR	Remote LCD annunciator, common controls, red, English
	RLCD-PG	Remote Annunciator: LCD text annunciator without common controls. Portuguese.
	RLCD-SP	Remote Annunciator: LCD text annunciator without common controls. Spanish.
	RLCD-R	Remote LCD annunciator, acknowledge/silence and lamp test buttons, red, English
	RLCD-C-PG	Remote Annunciator: LCD text annunciator with common controls. Portuguese.
	RLCD-C-SP	Remote Annunciator: LCD text annunciator with common controls. Spanish.
	R-LED	Remote alarm indicator
	RLED24(R)	Remote LED annunciator, 24 zones, white (red)
	RLED-C(F)	Remote LED annunciator, 16 zones, common controls, white, (French)
	RLED-CR	Remote LED annunciator, 16 zones, common controls, red, English
	RLED-C-PG	Remote Annunciator: 16-pair LED zone annunciator with common controls. Portuguese.
	RLED-C-SP	Remote Annunciator: 16-pair LED zone annunciator with common controls. Spanish.
	RPM	Reverse polarity module
	SMK	Smoke power converter module

Manufacturer	Model	Description
Gentex	AVSM-R [1]	Synchronization control module, red
	AVSM-W [1]	Synchronization control module, white
System Sensor	MDL3 [1]	Synchronization control module
Wheelock	DSM-12/24-R [1]	Synchronization control module, red

[1] Synchronization is limited to a single circuit.

Table 7: External power supplies

Manufacturer	Model	Description
Edwards	BPS6A, EBPS6A, MIRBPS6A	Booster power supply, 6.5 A, 120 V, 50/60 Hz
	BPS6A/230, EBPS6A/230, MIRBPS6A/230	Booster power supply, 6.5 A, 230 V, 50/60 Hz
	BPS6AC, MIRBPS6AC	Booster power supply, 6.5 A, 120 V, 50/60 Hz
	BPS6CAA, MIRBPS6CAA	Booster power supply, 6.5 A, 120 V, 50/60 Hz (California)
	BPS10A, EBPS10A, MIRBPS10A	Booster power supply, 10 A, 120 V, 50/60 Hz
	BPS10A/230, EBPS10A/230, MIRBPS10A/230	Booster power supply, 10 A, 230 V, 50/60 Hz
	BPS10AC, MIRBPS10AC	Booster power supply, 10 A, 120 V, 50/60 Hz
	BPS10CAA, MIRBPS10CAA	Booster power supply, 10 A, 120 V, 50/60 Hz (California)
	MIRAPS6A	Auxiliary power supply, 6.5 A, 120 V, 50/60 Hz
	MIRAPS6A/230	Auxiliary power supply, 6.5 A, 230 V, 50/60 Hz
	MIRAPS10A	Auxiliary power supply, 10 A, 120 V, 50/60 Hz
	MIRAPS10A/230	Auxiliary power supply, 10 A, 230 V, 50/60 Hz

Table 8: Genesis synchronization modules

Manufacturer	Model	Description
Edwards	GSA-CC1S	Auto-sync output module
	GSA-MCC1S	Auto-sync output module
	MG1M, EG1M, G1M	Genesis signal master module
	MG1M-RM, EG1M-RM, G1M-RM	Genesis signal master - remote mount

Table 9: CMS receivers

Manufacturer	Model	Format
Ademco	685	Contact ID
FBII	CP220	Contact ID
Osborne-Hoffman	OH 2000E	Contact ID, TCP/IP[1]
Bosch	D6600	Contact ID
Bosch	D6686	IP Contact ID (adds IP to the D6600)
Sur-Gard	SG-MLR1 and MLR2	Contact ID
MCDI	TLR and TLR+	Contact ID

[1] Using this device as a network receiver (TCP/IP) does not comply with CAN/ULC-S559 3rd edition requirements.

Table 10: SA-DACT compatible cellular capture modules

Manufacturer	Model	Format	Agency
Bosch	B465	IP/Cellular Contact ID	UL
DSC	3G4010	Cellular/Telco	ULC
Honeywell	IPGSM-4G	IP/Cellular Contact ID	UL
Telguard	TG-7FS	Telco/Cellular Contact ID	UL

Contact information

For contact information, see www.kiddelifesafety.com.